


## AX 2012 5.0.0.3 and Lascript 10 Error: "The Remote Server Returned an Error: (404) Not Found."

Alice Petruzzella - 2024-04-10 - Comments (0) - AX 2012 FAQs



# Formpipe.

When clicking **Validate settings** in Lascript Connector for AX 2012 while using Lascript 10, the following error message might occur:

Error

Lascript Web server

The remote server returned an error: (404) Not Found.

Web server is not responding.

The **Web server** is an optional setting in AX 2012 while using Lascript 10. However, if it is configured improperly, this error will occur.

When clicking **Validate settings**, a job is sent to Lascript to test the connection. The validation will be successful if the Lascript server receives the request and returns a response to Lascript Connector within a specified period.

## Solution

The following are the settings that should be reviewed and configured to have a successful **Web server** connection between Lascript Connector for AX 2012 and Lascript 10.

These can be applied to your custom configuration as appropriate.

1. You must have a **Web server** input module configured in your Lascript configuration. The **Timeout** field will determine the period of time for the connection validation.
2. The port number used in the Lascript configuration **Web server** input module and the **Web port** field in the **Lascript AX Parameters** must match.
3. Lascript must respond. Therefore, once the job is received through the **Web server** input, it must reach a **Form engine** and match a form with a PDF sheet.

4. The PDF output must be sent to **System > Preview destination**.

5. Once Lasernet Connector for AX 2012 receives Lasetnet's response, the **Validate settings** will be successful, and the error will be resolved.

## Additional Information

Attached to this article is a sample Lasetnet Configuration for a successful connection between the AX 2012 Lasetnet Connector and Lasetnet 10.

For advice on how to implement the solution to your custom configuration, reach out to your Lasetnet partner or contact us via the **Create Ticket** button on our Support Portal.

### Attachments

- [AX2012\\_LN10\\_WebServer\\_WebService\\_SampleSetup.Inconfigx \(554.73 KB\)](#)